

## Pulse Valve Controller AC220V Dust Collector



Pulse Valve Controller AC220V Output For Cleaning Dust Control Device 8 lines

Rating: Belum di-rating  
[Ajukan pertanyaan untuk produk ini](#)

### Deskripsi

Pulse Online Deashing Controller AC220V Output For Cleaning Dust Control Device 8 lines

QHK-8A Input voltage is AC220V, output voltage is AC220V



Online deashing controller is the main equipment of the bag type dust collector cleaning system .

The special voltage could be customized.

Its output signal directly controls the pulse jet valve . Made by high technology , it is of high quality and has Long service life .

The item adopts intelligent microprocessor circuit design so it is flexible control , stable performance , operation visually and convenient , without any operation to adjust the potentiometer .

It also adopts the latest anti - jamming design , ensure the system stability , more reliable .

## Quick Check

- 1) Body Material : engineering plastic
- 2) Weight : 1.0 kg
- 3) Working medium : Air
- 4) Output Pulse Width adjustment range : 50ms-2500ms
- 5) Temperature range : -25°C +60°C
- 6) Rated output current : 1A
- 7) Size : 160\*160\*90mm
- 8) No violent vibration or shock
- 9) Rated input voltage : AC220V
- 10) Rated output voltage : AC220V DC24 optional

## Specification

1. Output Pulse Width adjustment range : 30ms-2500ms
2. Color : transparent
3. Input Material: Air
4. Body Material : engineering plastic

Rated input voltage : AC220V  
Rated output voltage : AC220V  
Long service life  
Anti-jamming design  
Easy to install

## 10. Simple operation